

Mixerförstärkare 100 Volt, 120 watt Monacor PA-312



Mixeförstärkaren Monacor 312 med en uteffekt på 120W är ett bra val då man behöver en förstärkare som ska driva en ljudanläggning i ett 100 voltssystem

- **120 watt**
- **3 mikrofoningångar**
- **1 mikrofoningång med talkoverfunktion**
- **2 Aux-ingångar för mobil/dator/CD-spelare**

Mono mixing amplifier 100 volt

1x 120WRMS

Silent operation due to fanless cooling concept

3 microphone inputs, one of which is a balanced input

Mic 1 with priority circuit and adjustable automatic talkover

2 aux inputs

1 telephone input for telephone systems with audio output

Speaker outputs via screw terminals

1 line output

Input and output level controls

2-way tone control for the output

48V phantom power supply for channel 1, can be switched on additionally

482mm (19") rack installation with supplied mounting brackets

Få din mixerförstärkare inom 3 dagar. Lägg i varukorgen direkt!

Output power 120WRMS, 160WMAX
Mic input 5mV/600 ohm
Line input -Aux input 350mV/10k ohm
Telephone input 1V/10k ohm
Speaker output 4-16 ohm, 70/100V
Frequency range 50-16,000Hz
Equalizer bass ± 10 dB/100Hz
Equalizer, treble ± 10 dB/10kHz
S/N ratio 66dB (mic)

80dB (aux)

THD $\leq 0.5\%$
Power supply 230V/50Hz/450VA
Dimensions 430x88x335mm, 2RS
Weight 7.8kg
Inputs
1 x 6.3mm/XLR (combo)

1 x 6.3mm jack (mic 1)

2 x 6.3mm jack (mic 2-3)

2 x RCA L/R (aux 1-2)

screw terminals (telephone)

Outputs 2 x RCA L/R (line out)

Artikelnummer 96993

-

-